START:

- Anslut antennerna
- Sätt i simkort
- Anslut till ström

INSTALLATION MED MOBIL:

Att installera med mobilen går snabbt och enkelt men vi rekommenderar att du gör det via webbläsare eftersom du annars lämnar WIFI anslutningen öppen för alla att komma åt.

- Ladda ner appen M-Sight Pro
- Följ anvisningarna nedan

Anslut din mobil till routerns WIFI

10:19	🖬 4G 💽
Inställningar Wi-Fi	
Wi-Fi	
✓ Router_F5B24C Osäkert nätverk	? (j
MINA NÄTVERK	
#Telia-8A7050	🔒 🗢 🚺
Kontorshotell29c	ê 🗢 i
ANDRA NÄTVERK	
#Telia-54A2F0	🔒 🗢 🚺
DIRECT-b4-HP M283 Las	🔒 🤶 🚺
DIRECT-D1-HP OfficeJet Pro 7740	ê 🗢 i
Sector Alarm	🔒 🗢 🚺
Annat	
Fråga om anslutning	Av >
Automatisk anslutning till kända nätverk kända nätverk är tillgängliga måste du vi manuellt.	. Om inga älja ett nätverk

Username: admin Password: password



Öppna appen och sedan Remote Maintenance



Tryck på Network Settings



Tryck på Bind the router



Välj 4G och tryck Next



Ange din operatörs APN



Klart

ull 🗢 📘

Ó

My Devices

INSTALLATION MED DATOR (REKOMMENDERAS)

Anslut din dator till routern Öppna din webbläsare Ange: 192.168.1.1 Användare: admin / Lösen: password

	Milesight							
	<u> </u> €							
	Login							

- Gå till Network sedan Interface sedan Cellular
- Ange din operatörs APN tryck Save när du är klar

Status	Link Failover	Cellular Port	WAN	Bridge	WLAN	Switch	Loopback	Help —
otatus	-							Cellular Settings
Network	Cellular Settings	IPv4		~				APN Enter the Access Point Name for cellular dial-up connection provided by local ISP.
	APN	servic	s.telenor.se					Username
DHCP	Username							Enter the username for cellular dial-up connection provided by
Firewall	Password							local ISP.
QoS	PIN Code							Password Enter the password for cellular
VPN	Access Number							dial-up connection provided by local ISP.
	Authentication Type	Auto		~				PIN Code
IP Passthrough	Network Type	Auto		~				Enter a 4-8 characters PIN code to unlock the SIM.
Routing	PPP Preferred							Access Number
VRRP	SMS Center							Enter the dial-up center NO. for cellular dial-up connection
DDNS	Enable NAT	Z						Authentientien Tune
	Roaming							Select from "Auto", "PAP",
System 🕨	Data Limit	0		MB				"CHAP", "MS-CHAP", and "MS-CHAPv2".
	Billing Day	Day	✓ of The Month					Network Type
Maintenance	Connection Setting							Select from "Auto", "4G Only", "3G Only", and "2G Only". Auto: connect to the network
	Connection Mode	Alwa	s Online	~				with the strongest signal automatically.
	Re-dial Interval(s)	5						4G Only: connect to 4G network only. And so on.
								PPP Preferred
	Save							The PPP dial-up method is preferred.
javascript:void(0)								SMS Center

- Tryck sedan WLAN
 Ändra SSID om du önskar
 Ändra Encryption Mode WPA-PSK
 Ange ett lösenord till WIFI (Key)
 Tryck Save & Apply när du är klar

Charture .		Link Failover	Cellular	Port	WAN	Bridge	WLAN	Switch	Loopback	Help —
Status		Linki alovoi	oonana	1 OIT		Dridge		owner	Loopbuok	Enable
	-	WLAN								Enable/disable WLAN.
Network		Frankla		_						Work Mode
Interface		Enable		<u> </u>						Select router's work mode. The options are "Client" and "AP".
Interface		Work Mode		AP	~					Scan
DHCP		BSSID	[24:e1:24:f5:b2:4	D					Click "Scan" button to search
E		Radio Type	ĺ	802 11n(2 4GHz) v					the nearby access point.
Firewall			l		, .					SSID
QoS		Channel	l	Auto	~					Fill in the SSID of the access point.
		Bandwidth	[20MHz	~					BSSID
VPN		SSID	[Router_F5B24C						Fill in the MAC address of the
IP Passthrough		Economico Modo	ſ		0.00%					access point. Either SSID or BSSID can be filled to joint the
		Encryption Mode	l	WPA-PSK/WPA	2-P3K *					network.
Routing		Cipher		Auto	~					Encryption Mode
1/000		Key	[Select encryption mode. The
VINF		SSID Broadcast		2						"WEP Open System", "WEP
DDNS				-						Shared Key", "WPA-PSK", "WPA2-PSK" and "WPA-
		AP Isolation	(PSK/WPA2-PSK".
System	•	Guest Mode	(Cipher
		Max Client Number	ĺ	10						Select cipher. The options are
Maintenance	•		l							"AES/TKIP".
		MAC Filtering								Кеу
		Time	ſ	Dischlad						Fill in the key(8-63 charactors)
		туре	l	DISADIRO	~					COLD Recedence
										When SSID broadcast is
		Save & Apply								disabled, other wireless
										and users have to enter the
										SSID manually to access to the
javascript:void(0)										wireless network.

Gå sedan till System, User Management och ändra lösenordet